Product specification Switch mode power supply SNT10014 Input range: 85 - 270 V_{AC} or 120 - 400V_{DC} Output range: 10.0 - 15.6 V_{DC} Boostfunction 120% max. 30s simply mounting on rail acc. to DIN46277 or wall mounting with screws Gleichstromversorgung Device protection, shutdown on overtemperature 75,0 Operating status shown by LED 0 Parallel operatin possible, polarity reversal protection, short circuit proof, overload and open ciruit protected Vibration proof, suitable for the tropics -exposy resin casted 100.0 Output separated according to VDE0551 Conforms to EMC and low voltage directive PFC according to IEC/EN 61000-3-2 CE-konform Safety according to VDE, EN, UL, CSA

Application

The switch mode power supplies of the SNT100 series are powerful and robust devices to power sensitive loads in a hard industrial environment.

These features result from the modern construction with a good radio shielding and high reliability integrated in a functional and stable casing.

The short circuit proof output DC voltage of this type can be adjusted from 10.0 to 15.6 V. The output current can rise up to 120% of rating, therefore this power supply is suitable for loads requiring high starting current.

Functional principle

In the power supply SNT10014 a flyback converter operates to transform the energy in two steps. During the conducting phase the diode is blocking, the inductor is energized and a magnetic field establishes.

There is no electrical transmission; the consumer load is supplied with energy from the capacitor. When the switching transistor opens, the blocking phase begins. The current in the inductor cannot change immediately, discharges through the diode and a negative voltage establishes at the inductor.

Now operating like a power source the inductor reloads the capacitor and supplies the consumer with energy. The energy flows from the inductor into the capacitor and the consumer and through the conducting diode back to the inductor.

Design

Completly embedded with resin in an aluminium housing for mounting on a rail or mounting on wall with screws.



Postfach 1521 D - 22905 Ahrensburg Phone: +49 4102 42082 Telefax: +49 4102 40930

+

Input

consumer

Accu

Filter

Input current limiter

> E-Mail : sales@feas.com Internet: www.feas.com

Please read the data sheets

and the operating instructions for further information Output